6.5 INCH (165 MM) 4 OHM SHAKER

PART #: LC62SH-4A

Bring life to your sound and add rumbling depth to your audio system! The LC62SH-4A from MISCO is a 6.5" shaker perfect for home theaters, gaming and military simulators, and even medical therapy and massage chairs. This driver uses a high-energy ferrite magnet, and sports dual lug terminals for easy system wiring modifications and custom setups.

- Shaker
- 6.5" (165 mm) steel basket diameter
- 50 watts, 4 ohm
- 1.5" copper voice coil, aluminum former
- Ferrite magnet, aluminum dust cap



Primary Specifications

Size, Nominal (inch & mm)	6" (152 mm)
Rated Impedance (Ω)	4
Sensitivity (dB SPL) [1]	N/A
Frequency Range (Hz)	15 - 150
Resonant Frequency (Fs) (Hz) +/- 15%	40

©2026 MISCO/Minneapolis Speaker Company Inc.

6.5 INCH (165 MM) 4 OHM SHAKER

PART #: LC62SH-4A

More Specifications

Application	Arcade Gaming, Casino Gaming, High-End Audio and Home Theater
RoHS Compliant	Yes
DC Resistance (Re) (Ω)	3.2
Program Power (W)	100

Small Signal Parameters

DC Resistance (Re) (Ω)	3.2
Resonant Frequency (Fs) (Hz) +/- 15%	40
Mechanical Q Factor (Qms)	14
Electrical Q Factor (Qes)	3.4
Total Q Factor (Qts)	2.60

Material Descriptions

Basket Type	Stamped steel
Terminal Size (mm)	5.2 x 0.5
Voice Coil Diameter (mm)	38.1
Voice Coil Wire Material	Copper
Voice Coil Former Material	Aluminum
Magnet Material	Ferrite
Magnet Weight (g)	568
Cone Body Material	Aluminum
Cone Surround Material	Treated cloth
Dust Cap Material	Aluminum
Net Weight (kg)	2.62





©2026 MISCO/Minneapolis Speaker Company Inc.